


Tactical Talker Dual Radio Handset



SPECIFICATIONS	
Part Number	G06A016-OFK
Product	Tactical Talker Dual Radio Handset
Ear Impedance	1000 ohms
Mic Impedance	150 ohms
Mil Spec	Meets or exceeds MIL-PRF-49078 (H-250)
Control	Radio A PTT: Pushbutton (mom) Radio B PTT: Pushbutton (mom) Volume Balance: Rotary Note: Rotating volume knob CCW will increase volume of Radio A while simultaneously decreasing volume of Radio B. Rotation in the CW direction does the opposite.
Cordage	Coil cord into Y-branch; straight leads from Y-branch
Connectors	Radio A: U-329 style 6-pin Radio B: U-329 style 6-pin Listen-Only Headset: 3.5mm barrel
Color	 Black
Weight	< 2 lbs

FEATURES:

- Y-Branch cable enables two independent connections to two separate radios
- Dual PTT buttons allow users to operate two radios at the same time
- Circuitry mixes signals from both radios and allows user to balance volume of each
- U-329 style 6 pin connector

